

AD-A146 644

SIMPLIFIED CONTINUED FRACTION CALCULATION OF SPHERICAL

1/1

BESSEL FUNCTIONS(U) ARMY ELECTRONICS RESEARCH AND

DEVELOPMENT COMMAND WSMR NM ATH. W J LENTZ SEP 84


UNCLASSIFIED

ERADCOM/ASL-TR-0152

F/G 12/1

NL





MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS-1963-A

12



TR-0152

AD

Reports Control Symbol
OSD - 1366

AD-A146 644


**SIMPLIFIED CONTINUED FRACTION CALCULATION
OF SPHERICAL BESSEL FUNCTIONS**

SEPTEMBER 1984

By

W. J. Lentz

DTIC FILE COPY



Approved for public release; distribution unlimited.



US Army Electronics Research and Development Command

Atmospheric Sciences Laboratory

White Sands Missile Range, NM 88002

84 10 15 001

NOTICES

Disclaimers

The findings in this report are not to be construed as an official Department of the Army position, unless so designated by other authorized documents.


The citation of trade names and names of manufacturers in this report is not to be construed as official Government indorsement or approval of commercial products or services referenced herein.

Disposition

Destroy this report when it is no longer needed. Do not return it to the originator.

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM	
1. REPORT NUMBER	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER	
ASL-TR-0152	AD-414 6 644		
4. TITLE (and Subtitle)		5. TYPE OF REPORT & PERIOD COVERED	
SIMPLIFIED CONTINUED FRACTION CALCULATION OF SPHERICAL BESSEL FUNCTIONS		Technical Report	
6. AUTHOR		7. PERFORMING ORG. REPORT NUMBER	
W. J. Lentz			
8. PERFORMING ORGANIZATION NAME AND ADDRESS		9. PROGRAM ELEMENT PROJECT TASK AREA & WORK UNIT NUMBERS	
Army Atmospheric Sciences Laboratory White Sands Missile Range, NM 88052		DA Task 1551211AH/1	
10. CONTRACTING OFFICE NAME AND ADDRESS		11. REPORT DATE	
Army Electronics Research and Development Fort Monmouth, NJ 07703		September 1964	
12. MONITORING AGENCY NAME & ADDRESS (if different from Contracting Office)		13. NUMBER OF PAGES	
		19	
		14. SECURITY CLASS. (of this report)	
		UNCLASSIFIED	
		15. DECLASSIFICATION/DOWNGRADING SCHEDULE	
16. DISTRIBUTION STATEMENT (of this Report)			
Approved for public release; distribution unlimited.			
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)			
18. SUPPLEMENTARY NOTES			
19. ABSTRACTS (Continue on reverse side if necessary and identify by block number)			
spherical Bessel function continued fraction algorithm			
20. ABSTRACT (Continue on reverse side if necessary and identify by block number)			
A technique of generating spherical Bessel functions of real or complex argument is developed. A negative simple continued fraction is defined and error corrections developed for the calculation of the continued fraction. FORTRAN IV programs for spherical Bessel functions of real and complex argument are presented. The technique is simple, fast, and of higher accuracy than comparable techniques currently in use to evaluate spherical Bessel functions.			

SECURITY CLASSIFICATION OF THIS PAGE(When Data Entered)



CONTENTS

1. INTRODUCTION.....	5
2. SIMPLE CONTINUED FRACTION.....	5
3. SIMPLIFIED FORMULAE.....	7
4. SPHERICAL BESSEL FUNCTIONS.....	9
5. FORTRAN PROGRAMS.....	11
LITERATURE CITED.....	13
APPENDIX. FORTRAN ALGORITHM LISTINGS.....	15

Accession For		
NTIS GRA&I	<input checked="" type="checkbox"/>	
DTIC TAB	<input type="checkbox"/>	
Unannounced	<input type="checkbox"/>	
Justification		
Re		
Distribution/		
Availability Codes		
Avail and/or		
Dist Special		
A-1		



1. INTRODUCTION

A continued fraction technique^{1 2} has been developed for the calculation of the ratios of spherical Bessel functions of complex argument used in Mie calculations.^{3 4} When the spherical Bessel functions of complex argument themselves are required, the same technique may be applied with several simplifications. Spherical Bessel functions of complex argument have wide ranging applications in physics, electronics, and meteorology. The purpose of this report is to develop the simplified formulae for the calculation of spherical Bessel functions of complex argument and to present several algorithms that correctly calculate the functions. The technique is essentially based on a new method of evaluating continued fractions.

There are now four distinctly different methods that allow one to evaluate a continued fraction. Three of these methods are detailed in Gautschi,⁵ and the fourth in Lentz.¹ The Lentz⁶ continued fraction algorithm is of much more general application than just spherical Bessel functions. This algorithm essentially transforms a continued fraction into an infinite product, whereas the previous three methods convert to infinite series or recursions that have stability problems.

2. SIMPLE CONTINUED FRACTION

A simple continued fraction may be defined as:

$$F = a_1 + \frac{1}{a_2 + \frac{1}{a_3 + \dots + \frac{1}{a_n} + \dots}} \quad (1)$$

¹W. J. Lentz, 1973, A New Method of Computing Spherical Bessel Functions of Complex Argument with Tables, ECOM 5509, AD 767223, US Army Atmospheric Sciences Laboratory, White Sands Missile Range, NM

²W. J. Lentz, 1976, "Generating Bessel Functions in Mie Scattering Calculations Using Continued Fractions," Appl Opt, 15:668

³W. J. Wiscombe, 1980, "Improved Mie Scattering Algorithms," Appl Opt, 19:1505

⁴G. Grehan and G. Gouesbet, 1979, "Mie Theory Calculations: New Progress, with Emphasis on Particle Sizing," Appl Opt, 18:3489

⁵W. Gautschi, 1967, SIAM, Rev 9, No 1

⁶W. J. Lentz, 1982, A Simplification of Lentz's Algorithm, ASL-TR-0118, US Army Atmospheric Sciences Laboratory, White Sands Missile Range, NM

where none of the a_i may be zero. The a_i may be complex or negative, and the n th convergent of the continued fraction is defined as:

$$F_n = a_1 + \frac{1}{a_2 + \frac{1}{a_3 + \dots + \frac{1}{a_n}}} \quad (2)$$

This simple continued fraction might better be called a positive simple continued fraction because all the terms are added. One method of evaluating equation (2) is to start at a_n , take the reciprocal and add to a_{n-1} until a_1 is reached. The only trick is to know at which a_n to start for a given accuracy. Unfortunately, two terms in the iteration process may cancel, or nearly cancel, causing unpredictable errors in the final answer. Let us therefore review a new technique to evaluate continued fractions.²

Let us make a further change of notation to define a simple continued fraction more compactly.

$$F_n = [a_1, a_2, a_3, \dots, a_n] \quad (3)$$

Lentz² has shown that this continued fraction may be transformed to an equivalent form, which begins at a_1 rather than some indeterminate a_n .

$$F_n = \frac{[a_1] [a_2, a_1] [a_3, a_2, a_1] \dots [a_n, a_{n-1}, \dots, a_1]}{[a_2] [a_3, a_2] \dots [a_n, a_{n-1}, \dots, a_2]} \quad (4)$$

Although this formula may appear complicated, one generates successive numerators and denominators by taking the reciprocal and adding to the previous numerator or denominator. A numerical example and an algorithm for equation (4) may be found in reference 6.

¹W. J. Lentz, 1976, "Generating Bessel Functions in Mie Scattering Calculations Using Continued Fractions," Appl Opt, 15:668

²W. J. Lentz, 1982, A Simplification of Lentz's Algorithm, ASL-TR-0118, US Army Atmospheric Sciences Laboratory, White Sands Missile Range, NM

Since the a_i might be negative, one will note that any given term $[a_i, a_{i-1}, \dots, a_1(\text{or } 2)]$ might be inaccurate due to cancellation of common digits in the sum. In this case, an algorithm improvement has been devised.²

$$\text{Let } [a_{m-1}, \dots, a_1] = \alpha$$

$$\text{If } [a_m, \dots, a_1] = \beta = a_m + 1/\alpha \approx 0$$

$$\text{then } [a_{m+1}, \dots, a_1] = \gamma = a_{m+1} + 1/\beta \approx \infty$$

$$\text{let } [a_{m+2}, \dots, a_1] = Z = a_{m+2} + 1/\gamma$$

$$\text{then } \zeta = \beta\gamma = \beta \frac{a_{m+1} \beta + 1}{\beta} = a_{m+1} \beta + 1 \quad (5)$$

ζ is the product of the next two terms. If β is identically zero, then ζ is one. If the next term is then:

$$Z = \frac{a_{m+2} \gamma + 1}{\gamma} = \frac{a_{m+2} (a_{m+1} \beta + 1) + \beta}{a_{m+1} \beta + 1} \quad (6)$$

$$Z = a_{m+2} + \beta/\zeta$$

Note that the above formulae apply to both the numerator and the denominator since the form is independent of whether a_1 or a_2 is used. In fact, accuracy can be increased by using the algorithm improvement any time a common number of digits cancel to reducing accuracy in the generation of β . When a given numerator such as β is equal to its corresponding denominator to the number of desired digits, the fraction may be said to have converged to the desired accuracy. Reasonable accuracy may also be obtained by only considering the case when β is identically zero, and the simpler algorithm will improve execution time significantly.

²W. J. Lentz, 1976, "Generating Bessel Functions in Mie Scattering Calculations Using Continued Fractions," Appl Opt, 15:668

3. SIMPLIFIED FORMULAE

The continued fraction representation for the ratio of Bessel functions of consecutive order is given by:

$$\frac{J_{v-1}}{J_v} = F = [a_1, a_2, \dots, a_n, \dots] \quad (7)$$

where the $a_n = (-1)^{n+1} 2(v+n-1)/x$, v is the order, and x is the argument. A simplification is possible in this case because every other term is of opposite sign. The alternating sign can be eliminated by transforming the simple continued fraction to a simple negative continued fraction using equation (5) of 3.10.1 of Abramowitz.⁷

$$F_n = a_1 + \frac{c_2}{c_2 a_2} + \frac{c_2 c_3}{c_3 a_3} + \frac{c_3 c_4}{c_4 a_4} + \dots + \frac{c_{n-1} c_n}{c_n a_n} \quad (8)$$

If $c_{2m} = -1$ and $c_{2m+1} = 1$ and $b_{2m} = a_{2m}$ and $b_{2m+1} = a_{2m+1}$

then

$$G_n = b_1 - \frac{1}{b_2} - \frac{1}{b_3} - \frac{1}{b_4} - \dots - \frac{1}{b_n} \quad (9)$$

which will be defined as a negative simple continued fraction. None of the b_i may be zero, but they may be complex or negative. In like manner, a new notation may be defined for the n th convergent G_n .

$$\begin{aligned} G_n &= [-] [b_1, b_2, \dots, b_n] \\ &= [b_1, -b_2, b_3, -b_4, b_5, -b_6, \dots, b_n] \end{aligned} \quad (10)$$

⁷M. Abramowitz, F. W. J. Olver, and H. A. Antosiewicz, 1965, Handbook of Mathematical Functions, M. Abramowitz and I. A. Stegun, editors, Applied Mathematics Series 55, chapters 3, 9, and 10, US Government Printing Office, Washington, DC

where the first equation is a negative simple continued fraction and the second equation an equivalent positive simple continued fraction.

The need for this additional complexity will become apparent when the formulae for the spherical Bessel functions is derived.

The equivalent algorithm for negative continued fractions is:

$$G_n = \frac{[-] [b_1] [b_2, b_1] \dots [b_n, \dots, b_1]}{[b_2] [b_3, b_2] \dots [b_n, \dots, b_2]} \quad (11)$$

The algorithm improvement for negative continued fractions follows directly from the definition of the b_m .

$$\zeta = \beta\gamma = b_{m+1}\beta - 1 \quad (12)$$

$$Z = b_{m+2} - \beta/\zeta \quad (13)$$

The above formulae may apply to either the numerator or denominator or both completely independently.

4. SPHERICAL BESSEL FUNCTIONS

One straightforward way to calculate the consecutive orders of Bessel functions by the continued fraction technique is to multiply appropriate ratios by an initial value

$$1/j_n = 1/j_0 \frac{j_0}{j_1} \frac{j_1}{j_2} \frac{j_2}{j_3} \dots \frac{j_{n-1}}{j_n} \quad (14)$$

The initial value for spherical Bessel functions of complex argument is easily calculated from equation 10.1.11 of Abramowitz.⁷

$$j_0(x) = \sin(x)/x \quad (15)$$

In terms of a negative continued fraction $b_m = 2(v+m-1)/x$ where $v = n + 0.5$ is the order and m is the number of the term in the continued fraction.

$$\text{Let } b_{n,m} = 2(n + m - 0.5)/x$$

This definition is exactly equivalent to the previous b_m , and it allows one to keep track of both the order of the Bessel function ratio and the order of the continued fraction term. Using this notation, the product of n continued fraction ratios and an initial value becomes:

$$1/j_n = 1/j_0 \frac{[-] [b_{1,1}][b_{1,2}, b_{1,1}] \dots [b_{n,1}][b_{n,2}, b_{n,1}] \dots}{[b_{1,2}] \dots [b_{n,2}][b_{n,3}, b_{n,2}] \dots} \quad (16)$$

Some of the terms in the numerator and denominator are identical and cancel; for example, $[b_{1,2}] = [b_{2,1}]$. The terms that are generally identical are:

$$\begin{aligned} [b_{s,m+1}]_{\text{num}} &= [b_{s-1,m}]_{\text{den}} \\ [b_{s,m+2}, b_{s,m+1}]_{\text{num}} &= [b_{s-1,m+1}, b_{s-1,m}]_{\text{den}} \\ &\dots \end{aligned}$$

A simple rule to use to understand the terms that are identical is to note that lower order denominators cancel the next higher order numerators. All of the denominators corresponding to the ratio of Bessel functions of a given order cancel all of the numerators of the next higher order ratio of Bessel functions. All that is left is the numerator of the ratio j_0/j_1 and the denominator of the ratio j_{n-1}/j_n . This cancellation is not approximate. Every term is exactly identical if the proper terms are considered. Let us consider a numerical example for clarification. Let $x = 1.0$ in $j_9(x)$.

⁷M. Abramowitz, F. W. J. Olver, and H. A. Antosiewicz, 1965, Handbook of Mathematical Functions, M. Abramowitz and I. A. Stegun, editors, Applied Mathematics Series 55, chapters 3, 9, and 10, US Government Printing Office, Washington, DC

$$1/j_9 = (3)(4.666)(6.785714286)(8.852631589)(10.88703924)(12.90814766) * \\ (14.92252955)(16.93298723)(18.94094367)(20.94720432)(22.95226093) * \\ \frac{(21)(22.95238095)}{(24.95643131)(26.95993017)} * 1/\sin(1) = (1.4913765 \times 10^{-9})^{-1} \\ \frac{(24.95643154)(26.95993017)}{(24.95643154)(26.95993017)}$$

Note that there are nine terms before the denominator begins, and convergence is rapid once the continued fraction is begun.

It is important to realize that the error correction algorithm improvement applies to the first nine terms above as well as to the terms in the numerator and denominator of the complete continued fraction. The application of the algorithm improvement is completely independent of what is happening elsewhere; and in a properly constructed algorithm, no loss of accuracy will occur due to cancellation of digits in addition or subtraction.

5. FORTRAN PROGRAMS

The first FORTRAN IV program in the appendix is a simplified version of the spherical Bessel function formulae developed above. The only error check is for a term being identically zero in either the numerator or denominator. In that case, the error bypass is implemented through the algorithm improvement as detailed in reference 6. If a given term is zero, the product of that term and the next in the algorithm improvement is one. Therefore, it is sufficient to simply skip the product and reciprocal.

The second FORTRAN IV program is essentially the same program modified slightly for complex arguments. The test for convergence is also appropriately modified. Both of these programs have been checked against tables of spherical Bessel functions and found to be more accurate than the tables. Remember that the final answer is scaled by powers of 10^{*50} so that overflow will not occur in the computer. The displayed answer must be adjusted to account for this if the values are used in computations.

²W. J. Lentz, 1982, A Simplification of Lentz's Algorithm, ASL-TR-0118, US Army Atmospheric Sciences Laboratory, White Sands Missile Range, NM

¹W. J. Lentz, 1973, A New Method of Computing Spherical Bessel Functions of Complex Argument with Tables, ECOM 5509, AD 767223, US Army Atmospheric Sciences Laboratory, White Sands Missile Range, NM

LITERATURE CITED

1. Lentz, W. J., 1973, A New Method of Computing Spherical Bessel Functions of Complex Argument with Tables, ECOM 5509, AD 767223, US Army Atmospheric Sciences Laboratory, White Sands Missile Range, NM.
2. Lentz, W. J., 1976, "Generating Bessel Functions in Mie Scattering Calculations Using Continued Fractions," Appl Opt, 15:668.
3. Wiscombe, W. J., 1980, "Improved Mie Scattering Algorithms," Appl Opt, 19:1505.
4. Grehan, G., and G. Gouesbet, "Mie Theory Calculations: New Progress, with Emphasis on Particle Sizing," Appl Opt, 18:3489.
5. Gautschi, W., 1967, SIAM, Rev 9, No 1.
6. Lentz, W. J., 1982, A Simplification of Lentz's Algorithm, ASL-TR-0118, US Army Atmospheric Sciences Laboratory, White Sands Missile Range, NM.
7. Abramowitz, M., F. W. J. Olver, and H. A. Antosiewicz, 1965, Handbook of Mathematical Functions, M. Abramowitz and I. A. Stegun, editors, Applied Mathematics Series 55, chapters 3, 9, and 10, US Government Printing Office, Washington, DC.

APPENDIX
FORTRAN ALGORITHM LISTINGS

FBESSEL.FR

```

1:      COMPILER DOUBLE PRECISION
2:      C      PROGRAM FBESSEL CALCULATES SPHERICAL BESSEL FUNCTIONS OF THE FIRST
3:      C      KIND BY LENTZ CONTINUED FRACTION WITH A CHECK FOR ZERO ONLY
4:      C      IN THE NUMERATOR AND DENOMINATOR CALCULATIONS
5:      C      SEE APPLIED OPTICS VOL 15, NO 3 MARCH 1976 P668.
6:      C*****
7:      INTEGER ICOUNT,N
8:      REAL V,XINC,AN,JO,JN,X,NUM,DEN,PDT,SCALE
9:      C*****
10:     1      TYPE "INPUT ORDER, ARGUMENT OF SPHERICAL BESSEL FUNCTION"
11:     ACCEPT N,X
12:     PDT=1.0
13:     V=FLOAT(N)+0.5
14:     NUM=0.0
15:     DEN=0.0
16:     SCALE=0.0
17:     AN=1.0/X
18:     XINC=2.0/X
19:     ICOUNT=0
20:     C      IF N IS ZERO, THE INITIAL VALUE SIN(X)/X IS USED
21:     IF(N.EQ.0) GOTO 20
22:     17      AN=AN+XINC
23:     NUM=AN-NUM
24:     IF(NUM.EQ.0.0) GOTO 18
25:     PDT=PDT*NUM
26:     NUM=1.0/NUM
27:     IF(ABS(PDT).LT.1.0D50) GOTO 18
28:     PDT=PDT*1.0D-50
29:     SCALE=SCALE-50.
30:     18      ICOUNT=ICOUNT+1
31:     IF(ICOUNT.LE.N) GOTO 19
32:     DEN=AN-DEN
33:     IF(DEN.EQ.0.0) GOTO 19
34:     PDT=PDT/DEN
35:     DEN=1.0/DEN
36:     19      IF(NUM.NE.DEN.OR.ICOUNT.LT.5) GOTO 17
37:     20      JO=SIN(X)/X
38:     JN=JO/PDT
39:     WRITE(10,100) JN,SCALE,X,V,ICOUNT
40:     100      FORMAT(1H,"JN=",D20.10," POWER OF 10 SCALE=",F6.0,/,1H,"X=",(E14.6),
41:     X " V=",F6.1," COUNT=",I5)
42:     GOTO 1
43:     END
44:

```

Identifier					References		
AN	8	17	22	23	32		
DEN	8	15	32	33	34	35	36
ICOUNT	7	19	30	31	36	39	
JN	8	38	39				
JO	8	37	38				
N	7	11	13	21	31		
NUM	8	14	23	24	25	26	36
PDT	8	12	25	27	28	34	38
SCALE	8	16	29	39			
V	8	13	39				
X	8	11	17	18	37	39	
XINC	8	18	22				
1	10	42					
100	41	39					
17	22	36					
18	24	27	30				
19	31	33	36				
20	21	37					

No Compilation Errors -- Terminated at 11:28:54 AM

FCBESSEL.FR

```

1:      COMPILER DOUBLE PRECISION
2:      C      PROGRAM FCBESSEL CALCULATES BESSEL FUNCTIONS BY FIRST RATIO METHOD
3:      C      AND SIMPLIFICATIONS WITH ONLY A CHECK FOR ZERO. NO ACCURACY IMPROVEMENT
4:      C      IS IMPLEMENTED
5:
6:      C*****
7:      REAL COUNT,V,SCALE
8:      COMPLEX XINC,AN,J0,JN,X,NUM,DEN,PDT
9:      C*****
10:     1      TYPE "INPUT N,COMPLEX X"
11:     ACCEPT N,X
12:     PDT=1.0
13:     V=FLOAT(N)
14:     NUM=0.0
15:     DEN=0.0
16:     SCALE=0.0
17:     AN=1.0/X
18:     XINC=2.0/X
19:     COUNT=0
20:     C      IF N IS ZERO, USE THE INITIAL VALUE SIN(X)/X
21:     IF(N.EQ.0) GOTO 20
22:     17      AN=AN+XINC
23:     NUM=AN-NUM
24:     IF(NUM.EQ.0.0) GOTO 18
25:     PDT=PDT+NUM
26:     NUM=1.0/NUM
27:     IF(ABS(REAL(PDT)).LT.1.050) GOTO 13
28:     PDT=PDT*1.0-50
29:     SCALE=SCALE-50
30:     18      COUNT=COUNT+1.0
31:     IF(COUNT.LE.V) GOTO 19
32:     DEN=AN-DEN
33:     IF(DEN.EQ.0.0) GOTO 19
34:     PDT=PDT/DEN
35:     DEN=1.0/DEN
36:     19      IF(COUNT.LT.5.0) GOTO 17
37:     C      THIS CHECK FOR THE COMPLEX NUMERATOR EQUAL TO THE COMPLEX
38:     C      DENOMINATOR MAY BE MACHINE DEPENDENT
39:     IF(REAL(NUM).NE.REAL(DEN).OR.AIMAG(NUM).NE.AIMAG(DEN)) GOTO 17
40:     20      J0=CSIN(X)/X
41:     JN=J0/PDT
42:     WRITE(10,100) JN,SCALE,X,V,COUNT
43:     100      FORMAT(1H,"JN=",2(D20.10)," POWER OF 10 SCALE=",F6.0,"/,1H,"X=",
44:     X 2(E14.6)," N=",F6.0," COUNT=",F8.0)
45:     GOTO 1
46:     END
47:

```

Identifier					References		
AN	8	17	22	23	32		
COUNT	7	19	30	31	36	42	
DEN	8	15	32	33	34	35	39
JN	8	41	42				
JO	8	40	41				
N	11	13	21				
NUM	8	14	23	24	25	26	39
PDT	8	12	25	27	28	34	41
SCALE	7	16	29	42			
V	7	13	31	42			
X	8	11	17	18	40	42	
XINC	8	18	22				
1	10	45					
100	44	42					
17	22	36	39				
18	24	27	30				
19	31	33	36				
20	21	40					

No Compilation Errors -- Terminated at 12:13:45 PM

DISTRIBUTION LIST

Commander
US Army Aviation Center
ATTN: ATZQ-D-MA
Fort Rucker, AL 36362

John M. Hobbie
c/o Kentron International
2003 Byrd Spring Road
Huntsville, AL 35802

Redstone Scientific Information Center
ATTN: DRSMI-RPRD (Documents)
US Army Missile Command
Redstone Arsenal, AL 35898

Commander
US Army Missile Command
ATTN: DRSMI-REM (R. C. Haraway)
Redstone Arsenal, AL 35898

Commander
US Army Missile Command
ATTN: DRSMI-RHC (Mr. Richard D. Milton)
Redstone Arsenal, AL 35898

Commander
HQ, Fort Huachuca
ATTN: CCH-PCA-LD (Tech Library)
Fort Huachuca, AZ 85613

Naval Weapons Center
Code 3918
ATTN: Dr. A. Shlanta
China Lake, CA 93555

Geophysics Officer
PMTIC Code 3250
Pacific Missile Test Center
Point Mugu, CA 93042

Meteorologist in Charge
Kwajalein Missile Range
PO Box 67
APO San Francisco, CA 96555

Ball Aerospace Systems Division
PO Box 1062, TT5
ATTN: Dr. Charles M. Bradford
Boulder, CO 80306

Dr. E. C. Nickerson, Manager
Mesoscale Modeling Program
NOAA/OWRM Rx8
325 Broadway
Boulder, CO 80303

Library, R-51 Technical Reports
NOAA/ERL
US Department of Commerce
325 S. Broadway
Boulder, CO 80303

National Center for Atmos Rsch
Mesa Library
PO Box 3000
Boulder, CO 80307

Dr. B. A. Silverman
Bureau of Reclamation
Mail Code D-1200
PO Box 25007, Denver Federal Center
Denver, CO 80225

Naval Training Equipment Center
ATTN: TIC Bldg. 2068
Orlando, FL 32813

US Army Materiel Systems
Analysis Activity
ATTN: DRXS-MP
APG, MD 21005

Commander
US Army Electronics Research
& Development Command
ATTN: DRDEL-CT
2800 Powder Mill Road
Adelphi, MD 20783

Commander
US Army Electronics Research
& Development Command
ATTN: DRDEL-IN
2800 Powder Mill Road
Adelphi, MD 20783

PREVIOUS PAGE
IS BLANK

Commander
US Army Electronics Research
& Development Command
ATTN: DRDEL-CG
2800 Powder Mill Road
Adelphi, MD 20783

Commander
Harry Diamond Laboratories
ATTN: DELHD-CO
2800 Powder Mill Road
Adelphi, MD 20783

Chief
Intel Mat Dev & Spt Ofc
ATTN: DELEW-WL-I
Bldg 4554-D
Fort George G. Meade, MD 20755

The Environmental Research
Institute of MI
ATTN: IRIA Library
PO Box 8618
Ann Arbor, MI 48107

Dr. A. D. Belmont
Research Division
PO Box 1249
Control Data Corp
Minneapolis, MN 55440

Commanding Officer
US Army Armament R&D Command
ATTN: DRDAR-TSS Bldg 59
Dover, NJ 07801

Commander
USA Elect Warfare Lab
ATTN: DELEW-DA (File Cy)
Fort Monmouth, NJ 07703

Commander
US Army Electronics R&D Command
ATTN: DELCS-S
Fort Monmouth, NJ 07703

Commander
US Army Satellite Comm Agency
ATTN: DRCPM-SC-3
Fort Monmouth, NJ 07703

Commander/Director
US Army Combat Survl & Target
Acquisition Laboratory
ATTN: DELCS-DT
Fort Monmouth, NJ 07703

6585th TG (AFSC)
ATTN: RX (Capt Stein)
Holloman AFB, NM 86330

Science and Technology Corp.
First National Tower, Suite 940
Las Cruces, NM 88005

TRASANA
ATTN: ATOR-TSL (D. Anguiano)
WSMR, NM 88002

Commander
US Army White Sands Missile Range
ATTN: STEWS-AG-TL
White Sands Missile Range, NM 88002

Rome Air Development Center
ATTN: Documents Section (TSTD)
Griffiss AFB, NY 13441

Dr. Jerry Davis
Dept of Marine, Earth, and Atmos Sci
PO Box 5068
North Carolina State University
Raleigh, NC 27650

US Army Research Office
ATTN: DRXRO-IP
PO Box 12211
Rsch Triangle Park, NC 27709

Commandant
US Army Field Artillery School
ATTN: ATSF-FD (Mr. Taylor)
Fort Sill, OK 73503

Commander
US Army Dugway Proving Ground
ATTN: STEDP-MT-DA-M
(Mr. Paul Carlson)
Dugway, UT 84022

Commander
US Army Dugway Proving Ground
ATTN: MT-DA-L
Dugway, UT 84022

US Army Dugway Proving Ground
ATTN: STEDP-MT-DA-T
(Dr. W. A. Peterson)
Dugway, UT 84022

Defense Technical Information Center
ATTN: DTIC-DDA-2
Cameron Station, Bldg. 5
Alexandria, VA 22314
12

Commanding Officer
US Army Foreign Sci & Tech Center
ATTN: DRXST-IS-1
220 7th Street, NE
Charlottesville, VA 22901

Naval Surface Weapons Center
Code G65
Dahlgren, VA 22448

Commander
USATRADOC
ATTN: ATCD-FA
Fort Monroe, VA 23651

Science and Technology Corp.
PO Box 7390
Hampton, VA 23666

Dept of the Air Force
5WW/DN
Langley AFB, VA 23665

US Army Nuclear & Cml Agency
ATTN: MONA-WE
Springfield, VA 22150

Dr. Eugene W. Bierly
Director, Division of Atmos Sciences
National Science Foundation
1800 G Street, N.W.
Washington, DC 20550

HQDA (DAEN-RDM/Dr. Gomez)
Washington, DC 20314

The Library of Congress
ATTN: Exchange & Gift Div
Washington, DC 20540

Mil Asst for Atmos Sci Ofc of
the Undersecretary of Defense
for Rsch & Engr/E&LS RM 3D129
The Pentagon
Washington, DC 20301

Dr. John L. Walsh
Code 6530
Naval Research Lab
Washington, DC 20375

END

FILMED

11-84

DTIC